

REPLACEMENT INSTRUCTIONS

STRAIGHT-ACTING JACK 2 WIRE WARNING SWITCH

THIS WARNING SWITCH KIT WILL BE USED TO REPLACE ANY 2-WIRE MAGNETIC WARNING SWITCH ON STRAIGHT-ACTING STYLE JACKS. THIS SWITCH KIT CANNOT BE USED TO REPLACE A 3-WIRE WARNING SWITCH.

THERE ARE THREE POSSIBLE SITUATIONS THAT CAN OCCUR WHEN REPLACING A SWITCH.

1. REPLACEMENT OF A 2-WIRE WARNING SWITCH THAT HAS A GRAY 2-PIN PACKARD TOWER. DISREGARD BOTH ADAPTERS, THEY ARE NOT NECESSARY.

3. REPLACEMENT OF A 2-WIRE WARNING SWITCH THAT HAS A 1-PIN PACKARD TOWER AND RING TERMINAL. USE BOTH ADAPTERS AS SHOWN BELOW.

2. REPLACEMENT OF A 2-WIRE WARNING SWITCH THAT HAS A BLACK 2-PIN PACKARD TOWER. USE THE RAP93245 ADAPTER, AS SHOWN BELOW.

THE RING TERMINAL OF THE ADAPTER CAN BE GROUND-ED AT THE SAME LOCATION AS THE ORIGINAL WARNING SWITCH, OR TO THE FRAME OF THE VEHICLE.

